

# Candle & Fancy Round Globes (Zigbee)

S9B15LED12-ZB / S9B15LED13-ZB  
S9E14LED12-ZB / S9E14LED13-ZB



## Features

- Zigbee 3.0 compliant
- Available in either E14 or B15 socket
- Warm White - 3000K
- On/off & dimming control via the app
- Customizable timers & schedules via the app
- Works with both Amazon Alexa and Google Assistant
- 3 year warranty



Candle

Fancy round

## Network/Device Requirements

Connectivity	Zigbee
Requirements	Mercator Ikuü zigbee hub
Protocol	IEEE 802.15.4
Wireless Frequency	2.4GHz
App Requirements	Mobile device running iOS or Android. (Refer to <a href="http://ikuu.com.au">ikuu.com.au</a> for minimum specs)

## Technical Specifications

	S9B15LED12-ZB	S9E14LED12-ZB	S9B15LED13-ZB	S9E14LED13-ZB
Globe Shape	Candle		Fancy round	
Socket	B15	E14	B15	E14
Max Load	4W			
Supply Voltage	220-240V a.c. 50Hz			
Standby Wattage	<0.05W			
Housing Colour	White			
Housing Material	Polybutylene terephthalate (enclosure) polycarbonate (diffuser)			
Weight	30g			
Dimensions (H x Diam)	112 mm x 38mm		90mm x 46mm	
Lumens	380lm			
Colour Range (CCT)	3000K			
CRI	>80			
Beam Angle	200°			
Dimmable	Via the app <sup>(1)</sup>			
Estimated Lifetime	30,000 hours			

<sup>(1)</sup> This luminaire is app dimmable only and must not be used in conjunction with other dimmers

This product is valid for 3 years warranty from the date of purchase. Please retain proof of purchase and contact our customer service team to make a claim. Please visit <https://www.mercator.com.au/product-support/warranty> for more information. For Mercator Ikuü contractor or end consumer support please visit [www.ikuu.com.au](http://www.ikuu.com.au) or contact our customer service team on 1300 552 255 or via email at [customer@mercator.com.au](mailto:customer@mercator.com.au)



\*Download the app using the QR code or visit the iOS or Google Play store.