

Rotary Dimmer Mechanism (Zigbee) Isaac series

SSWRM-ZB



Features

- Zigbee 3.0 compliant
- No neutral wire required
- Trailing edge dimmer
- Interchangeable with most popular brands
- White LED to indicate switch status
- Includes push button
- Extra slim dial
- Combination head screws
- On/off & dimming control via the app
- Compatible with most popular brands, including 1, 2 or
- Customizable timers & schedules via the app
- Works with both Amazon Alexa and Google Assistant
- 3 year in-home warranty


Network/Device Requirements

Connectivity	Zigbee
Requirements	Mercator Ikuü Zigbee hub
Protocol	IEEE 802.15.4
Wireless Frequency	2.4GHz
App Requirements	Mobile device running iOS or Android.
	(Refer to ikuu.com.au for minimum specs)

Technical Specifications

No	
250V a.c. 50Hz	
< 1W	
LED: 5W -200W	
Incandescent: 5W -200W	
Trailing edge	
0-100% (limits set via app)	
IP20 (Indoor use only)	
3.5mm ²	
(can fit up to 3 x 1.5mm ² wires per terminal)	
White button, Yellow housing	
Yellow	
Polycarbonate	
Brass	
39g	
24mm x 40mm x 60mm	
AS/NZS 4268, AS/NZS 60669.1,	
AS/NZS 60669.2.1, AS/NZS 2772.2,	
CISPR 15, CISPR 32	

Wiring Diagram



Note: A momentary press switch returns to the open position when released. If an external switch cannot be installed, leave the 'P' control terminal unconnected.



This product is valid for 3 years in-home warranty from the date of purchase. Please retain proof of purchase and certificate of compliance from the installation to make a claim. Please visit https://www.mercator.com.au/product-<u>support/warranty</u> for more information. For Mercator Ikuü contractor or end consumer support please visit www.ikuu.com.au or contact our customer service team on 1300 552 255 or via email at customercare@mercator.com.au







