

Combination Sensor (Zigbee)

SSWMPIR-ZB



This product must be installed by a licensed electrician

Features

- Zigbee 3.0 compliant
- Neutral required
- Integrated with PIR/LUX/Temperature/Humidity sensor
- Blue LED to indicate switch status
- Retrofit to standard mounting brackets
- White, UV resistant material
- Scene control via the app
- Works with both Amazon Alexa and Google Assistant
- 3 year in-home warranty



Network/Device Requirements

Connectivity	Zigbee
Requirements	Mercator Ikuü Zigbee hub
Protocol	IEEE 802.15.4
Wireless Frequency	2.4GHz
App Requirements	Mobile device running iOS or Android.
	(Refer to ikuu.com.au for minimum specs)


Technical Specifications

reclinical Specifications	
Colour	White
Neutral Required	Yes
Supply Voltage	250V a.c. 50Hz
Standby Wattage	<0.05W
Operating Load	LED: 400W
	Incandescent (Halogen): 1500W
	Motor Rating: M40
Rated Ambient	25°C
Temperature	
IP Rating	IP20 (indoor use only)
Terminal Size	6mm ²
	(can fit up to 3 x 2.5mm² wires per terminal)
Rear Colour	Yellow
Housing Material	Polycarbonate
Contact Material	Brass
Weight	160g
Dimensions	115mm x 74mm x 44mm
Cut-out Dimensions	80mm x 50mm
Mounting Centres	84mm
Compliance /	AS/NZS 4268, AS/NZS 60669.1,
Standards	AS/NZS 60669.2.1, AS/NZS 2772.2,
	CISPR 15, CISPR 32

Included Accessories

Faceplate, Cut-out template, Mounting screws

Wiring Diagram





This product is valid for 3 years in-home warranty from the date of purchase. Please retain proof of purchase and certificate of compliance from the installation to make a claim. Please visit https://www.mercator.com.au/product-support/warranty for more information. For Mercator Ikuü contractor or end consumer support please visit www.ikuu.com.au or contact our customer service team on 1300 552 255 or via email at customercare@mercator.com.au







