

# COB Strip Light (Zigbee)

SMLD552-ZB



## Features

- Uses Zigbee communication protocol, requires Mercator Ikuu hub
- 10mm, 3 pin LED strip
- CCT control from warm white 2700K to cool white 6500K
- 640 LEDs per metre
- Cuttable at 50mm intervals
- 24V wall adapter & 1.5m cable supplied
- On/off & dimming control via the app
- Customizable timers & schedules via the app
- Works with both Amazon Alexa and Google Assistant
- 3 year warranty



## Network/Device Requirements

Connectivity	Zigbee
Requirements	Mercator Ikuu Zigbee hub
Protocol	IEEE 802.15.4
Wireless Frequency	2.4GHz
App Requirements	Mobile device running iOS or Android. (Refer to <a href="http://ikuu.com.au">ikuu.com.au</a> for minimum specs)

## Included Accessories

Power supply with cable, Zigbee controller, Re-joining connector, Double sided adhesive tape

## Technical Specifications

	SMLD552-ZB
Supply Voltage	24V DC (adaptor supplied)
Standby Wattage	<0.05W
Max Load	36W
IP Rating	IP44 (Strip only, excludes ends)
Colour	White
Dimensions	10mm x 5m
Power Cable (supplied)	1.5m length
Lumens	3000lm
Colour Range (CCT)	Adjustable, 2700K to 6500K
Dimmable	Via the app <sup>(1)</sup>
Compliance / Standards	AS/NZS 60958.2.1, AS/NZS 61347.2.11, AS/NZS 4268, CISPR 15 Adaptor provided complies with AS/NZS 61347.2.13

<sup>(1)</sup> This luminaire is app dimmable only and must not be used in conjunction with other dimmers



This product is valid for 3 years warranty from the date of purchase. Please retain proof of purchase and contact our customer service team to make a claim. Please visit <https://www.mercator.com.au/product-support/warranty> for more information. For Mercator Ikuu contractor or end consumer support please visit [www.ikuu.com.au](http://www.ikuu.com.au) or contact our customer service team on 1300 552 255 or via email at [customercare@mercator.com.au](mailto:customercare@mercator.com.au)

\*Download the app using the QR code or visit the iOS or Google Play store.

[www.ikuu.com.au](http://www.ikuu.com.au)

